

THE BABY SWITCH



The Baby Switch is for all venues! Theatres are now having to have Hard Non Dim (relays) for their LED fixtures – that is what the baby switch does. It's a DMX controlled 25 Amp Relay.

The Baby Switch can control up to (8) 250 watt LED fixtures. It can be used for any device that requires DMX controlled 120 volt power up to 20 amps.

The Baby Switch features an LCD display for selecting the DMX control channel. It can also be set to two (2) other operating modes that will activate the relay when DMX is present and when any DMX channel is above 1%. There is a hold time for modes 2 and 3, maintaining the relay closure after DMX is no longer present.

Modes (set by jumpers)

Basic: Relay triggers when DMX is present (no channel level).
- hold time 20 minutes after DMX goes away.

Merge: Relay triggers when any DMX channel is above 1%.
- hold time 20 minutes after DMX goes away.

Non DIM: Relay triggers on a set DMX address level 10% – turns off when DMX is 0%.
DMX channel is set via up/down push buttons and LCD display screen.

- LED indicator for DMX present (flashing) and DMX active (solid).
- LCD screen to display DMX channel address.
- Flush mount 5 pin DMX IN and Thru XLR connectors.
- Flush Mount Powercon connectors are use for power in and out.



Established in 1985, Scenework's primary focus was the service and maintenance of dimming systems and control equipment of the Canadian theatrical and television industry. Scenework's approach to equipment maintenance has set the standard for quality and reliability in the industry for twenty-eight (28) years. Shaped by our commitment to service, our expertise in understanding lighting system engineering is coupled with a clear understanding of the "real time" needs of our clients. We

provide immediate and expert solutions to service problems. Scenework has been a Strand Lighting Inc. dealer since 1988 and authorized service centre for Strand Lighting products in Canada. All our service staff are factory-trained Strand Lighting service technicians whose combined total of expertise exceeds 100 years. Response time to service calls is usually the same day or next day depending on travel restrictions and weather conditions. Scenework is available at all times for response to service calls either by immediate direct contact, answering services or mobile communication. Scenework will make available to its customers, dependent on circumstances, equipment on an "on-loan" basis. Scenework is also available to service equipment from other dimming manufacturers.

449 Laird Road, Unit #3, Guelph, Ontario N1G 4W1
tel: 519-837-8367 • fax: 519-837-2487
www.scenework.com • e-mail: info@scenework.com